

## DIGITAL COAX WALL BOX

RCA connector for Digital Coax wire

### APPLICATIONS

- Receiver (Tuner)
- TVs: CRT, LCD, Plasma, or DLP
- DVD: Standard or High-Definition
- Cable or Satellite
- Gaming

### SYSTEM

PWR™ Series Wire: 1 Pair  
+  
Digital Coax Wall Box

### ADVANTAGES

#### Wire + Connector

- Installs on surface of walls and ceilings
- No special installation tools required
- No soldering
- Paintable

#### Wire

- No stripping of insulation or exposed conductors
- Easily concealed foil-thin wire bends to any angle

### FEATURES

#### Wire

- Pre-terminated wire ensures highest quality and easy installation via a snap fit
- Patented 'Pattern Wave Conductor' technology results in a uniquely formed length of copper wiring that transmits signals without any noticeable loss in the quality of picture or sound

#### Connector

- Simple slide on connection between FlatWire and wall box
- Compatible with industry standard RCA patch cords
- Paintable finish to match decorative needs
- Durable powder-coated steel shell
- Corrosion-free

### SPECIFICATIONS

#### Wire

- Length: 10' & 20' (3m & 6m)
- Width: 0.645" (16.383mm)
- Thinness: 0.015" (0.381mm)
- Gauge: 28AWG or 12SEG (Skin Equivalent Gauge®)
- Oxygen Free Copper
- 2 Conductors (1 Pair)
- Resistance: 0.546 Ω (10')
- Capacitance: 18.700 pF/ft @ 100 KHZ
- Inductance: 0.200 μH/ft @ 100 KHZ
- Impedance: 75 Ω

#### Connector

- Length: 2.640" (67.056mm)
- Width: 2.430" (61.722mm)
- Height: 1.000" (25.400mm)
- Impedance: 75 Ω

